

BURNDY - INDENTOR DIES FOR MAC COPPER CONNECTORS

CableSize	DieIndex	Y34A	Y34B	Y46	Y44B	Y48B	Y486RB
6	7	A6CD Y34PR	B6CD Y34PR	-	-	-	-
4	8	A4CD Y34PR	B4CD Y34PR	-	-	-	-
2	10	A2CD Y34PR	B2CD Y34PR	-	-	-	-
1	11	A1CD Y34PR	B1CD Y34PR	-	-	-	-
1/0	12	A25D Y34PR	B25CD Y34PR	P25D P34PR	E25D Y44PR	-	-
2/0	13	A26D Y34PR	B26CD Y34PR	P26D P34PR	E26D Y44PR	-	-
3/0	14	A27D Y34PR	B27CD Y34PR	P27D P34PR	E27D Y44PR	-	-
4/0	15	A28D Y34PR	B28CD Y34PR	P28D P34PR	E28D Y44PR	C28D Y48PR	F28D Y48PR
250	16	A29D Y34PR	B29CD Y34PR	P29D P34PR	E29D Y44PR	C29D Y48PR	F29D Y48PR
300	17	A30D Y34PR	B30CD Y34PR	P30D P34PR	E30D Y44PR	C30D Y48PR	F30D Y48PR
350	18	A31D Y34PR	B31CD Y34PR	P31D P34PR	E31D Y44PR	C31D Y48PR	F31D Y48PR
400	19	A32D Y34PR	B32CD Y34PR	P32D P34PR	E32D Y44PR	C32D Y48PR	F32D Y48PR
500	20	A34D Y34PR	NO NEST Y43PR	P34D P34PR	E34D Y44PR	C34D Y48PR	F34D Y48PR
600	22	-	-	P36D P34PR	E36D Y44PR	C36D Y48PR	F36D Y48PR
750	24	-	-	P39D P34PR	E39D Y44PR	C39D Y48PR	F39D Y48PR
800	25	-	-	P40D P34PR	E40D Y44PR	C40D Y48PR	F40D Y48PR
1000	27	-	-	P44D P34PR	NO NEST Y44PR	C44D Y48PR	F44D Y48PR
1500	31	-	-	-	-	C46D Y48PR	F46D Y48PR
2000	34	-	-	-	-	C48D Y48PR	F48D Y48PR